



COMPACT HIGH-END STEREO NETWORK/CD/DAB/FM RECEIVER  
WITH A MAX. POWER OUTPUT OF 150 WATTS IN HI-RES QUALITY



COMPACT HIGH-END STEREO  
NETWORK/CD/DAB/FM  
RECEIVER WITH A MAX. POWER  
OUTPUT OF 150 WATTS IN  
HI-RES QUALITY

- Amplifier and digital-to-analogue converter in certified Hi-Res quality
- MAGNAT STREAMING APP controls music streaming (Spotify™), internet radio and multiroom functions
- High-quality CD drive with precision laser unit and DAB+/FM tuner with large station memory
- Bluetooth® streaming (4.1) with the high-end audio standard Qualcomm® aptX™
- Digital inputs (e.g. for direct connection of a TV) plus additional analog inputs and subwoofer output
- Sturdy full-metal enclosure with solid aluminium front plate and controls



## CD PLAYER:

- Repeat function (title/CD)
- Random function
- Title programming (up to 99 titles)
- CD audio, MP3 and WMA playback
- Supports CD text and ID3 tag

## NETWORK FUNCTIONS:

- Internet radio
- Spotify™ audio streaming
- DLNA audio streaming
- Multiroom functions
- Own MAGNAT STREAMING APP for comfortable control of network functions

## POWER AMPLIFIER AND POWER SUPPLY:

- Two analogue high-level inputs
- Additional 3.5 mm audio input on the front panel for connecting portable devices
- Digital inputs (1 x optical and 1 x coaxial) for sampling frequencies up to 192 kHz/24 bits, Hi-Res certified
- Bluetooth® input (4.1) supports the high-end audio standard Qualcomm® aptX™
- Analogue output for connecting a powered subwoofer
- Record Out fixed level output
- Headphone output with 6.3 mm jack
- Output power: 35 watt of sine power per channel (4 ohms)
- Elaborate mains adapter
- Shielded toroidal transformer
- Standby power supply for low power consumption in standby mode

## MISCELLANEOUS:

- Sturdy full-metal enclosure with solid, brushed aluminium front
- Solid aluminium controls
- Stable feet with damping rubber insert
- Readable, two-line clear text display with adjustable brightness (3 stages)
- System remote control for all functions

## FM/DAB TUNER:

- Digital DAB/DAB+ tuner
- FM tuner
- RDS/radio text function
- 40 programmable station presets each for DAB/DAB+ and FM
- Station search (DAB)
- Automatic scanning function (FM)







## MC 200

Compact high-end stereo NETWORK/CD/DAB/FM receiver with a max. power output of 150 watts in Hi-Res quality

### TUNER:

**FREQUENCY RANGE FM**  
87.5 – 108 MHz

**FREQUENCY RANGE DAB/DAB+**  
174.928 – 239.2 MHz (Band III)

**SENSITIVITY FM**  
-108 dBm

**SENSITIVITY DAB/DAB+**  
-100 dBm

### CD PLAYER:

**COMPATIBLE DISC FORMATS**  
CD-Audio, CD-R, CD-RW, MP3, WMA

### AMPLIFIER:

#### OUTPUT POWER

Nominal power:  
20 Hz – 20 kHz, THD < 1.0%, 4 Ω 2 x 35 W  
20 Hz – 20 kHz, THD < 1.0%, 8 Ω 2 x 25 W  
Peak power: 1 kHz, 4 Ω 2 x 75 W

#### FREQUENCY RESPONSE

CD/Aux/Line 10 Hz – 80 kHz (-3,0 dB)  
20 Hz – 20 kHz (+/-0,5 dB)

#### S/N RATIO

CD/Aux/Line 98 dB (A)  
Digital inputs -

#### INPUT SENSITIVITY

Aux/Line 470 mV/100 kΩ

#### DIGITAL INPUTS

1x optical (Toslink™)  
1x coaxial (cinch)  
Supported sampling frequencies: 44.1/48/88.2/96/176.4/192 kHz  
Supported bit depths: 16/24 bits

### BLUETOOTH® INPUT

Bluetooth® 4.1 / Qualcomm aptX®

### NETWORK INPUT

WLAN: 2.4 GHz, 802.11 b/g/n, WPA2, 300Mbps  
(up to 192 kHz/24 Bit)  
LAN: RJ45

Control over MAGNAT STREAMING APP (available for iOS und Android)  
network player, DLNA player, internet radio, multiroom functionality

### OPERATING FREQUENCY

2402 - 2480 MHz

### MAX. EMITTED POWER ACCOURDING TO EN 62479

15,73 dBm

### MAX. POWER CONSUMPTION

Maximum: 130 W, Standby: < 0,5 W

### AVAILABLE COLOURS

Black

### DIMENSIONS (WxHxD)

Main unit: 277 x 132 x 330 mm  
Incl. controls and connectors: 277 x 132 x 370 mm  
Remote control: 45 x 175 x 20 mm

### WEIGHT

5.8 kg

### ART.NO. / EAN

149 521 / 40 18843 49521 7

### SCOPE OF DELIVERY

MC 200 Receiver  
Remote control incl. batteries  
FM/DAB areal antenna  
Power cord  
Instruction manual

